	85 Kenilworth Road, London, HA8 8XA, United Kingdom		
N habbat	<b>L</b> +44 20 8004 955		
	@ info@ShabbatSmart.cor		
JMART	(III) www.ShabbatSmart.com		

Wi-Fi SE	TUP
----------	-----

- POWER ON the ShabbatSmart Hot Water controller.
- open your Phone's Wi-Fi settings.
- Connect to a \*Shelly\* network (the Wi-Fi controller's internal network).
- Open a browser on your phone and type 192.168.33.1 in the address bar. This will open the Wi-Fi controller's Dashboard.
- on the dashboard, select 'Network'
- on the drop-down menu select 'WiFi'.

		18:01 Sholli			18:02	,⊪≎⊮
		switch_0			switch_0	• • • • • •
<b>≎</b> ₩i-Fi		<b>E</b>			Wifi	~
ShellyPlus1- A8032ABC37C4	÷	Channel settings	Timers	Schedules	Access point	~
DIRECT-9D-HP OfficeJet Pro 9020	<b>₽</b> <del>?</del>	Webhooks	Device	Networks	Cloud Bluetooth	~ ~
iKettle	÷				Mqtt	~
Tenways	• <del>?</del>					<b>.</b>
Tenways EAP Wi-Fi settings	<b>₽</b> \$				Channel settings	imers Schedules
		Id: A8032ABC37C4 Version: 0.7.0 Allterco Robotics			Id: A80	032ABC37C4
		АА	192.168.33.1	S	Allter	co Robotics
		$\langle \rangle$	Û		192.	168.33.1

.11 🗢 14

Ilu

ACCOUNT orgot Password ?

#### SHABBAT SMART LTD



#### C +44 20 8004 9558 @ info@ShabbatSmart.com www.ShabbatSmart.com



Next enable Wi-Fi 1 and enter the network • username and password. Please note that this device only supports a 2.4GHz network.

Sh

- Next, connect your phone to the same Wi-Fi ٠ network as the Wi-Fi switch.
- Next, download the Shelly Cloud App from the App ٠ Store or Google Play.

18:03	•II 4G 🗲	18:04			IG 🚺	18:05	
	* <b>•</b> T	Search	Shelly (	Cloud			
Networks		Shelly	Allterco Ro	botics EOOD	ተ		
Wifi	^		OPEN		Ċ	6	Sha
Disconnected Wifi 1		31 RATINGS <b>1.8</b>	AGE <b>4+</b>	CATEGORY	E		
Enable:		***	Years Old	Lifestyle	Allter		
Connect the Shelly device	e to an existing	What's Nev	N	Version His	story		LUG
		Version 1.4.5		1mc	o ago	:	Your E-mail
ີ ຈີ່ ShabbatSmart		Discovering dev	ices improverr	ient			
123456789		Preview				Ê	Password
Open Network:						0-	LOG
Set static IP address: 🔵		Contro	ol your	All y	your (		
Apply		from any	where	dev in one	e place		CREATE NEV
							F
Wifi 2					11:47		
Enable: 🔵					Wing room		
Id: A8032AB Version: C Allterco Rol	C37C4 0.7.0 botics						
192.168.33.	1	Today Games	Apps	Arcade	Search		

85 Kenilworth Road, London, HA8 8XA, United Kingdom







- Next, create your Shelly account.
- Select the location/country where the device is installed at (important for Sunset related time scheduling).
- Next, log in to your Shelly account.
- On the main page select 'Add Room'.
- Name the room and select an image for the Room.
- Save Room

85 Kenilworth Road, London, HA8 8XA, United Kingdom +44 20 8004 9558

### ● +44 20 8004 9558 @ info@ShabbatSmart.com ● www.ShabbatSmart.com



Shabbat

- Under "Discovered Devices" 'click to add'.
- Name your device.
- Select a Room for the device.
- under CHOOSE RELAY USAGE, select Relay.
- Save the changes and accept the connection to the cloud.
- Next, Select the device.

85 Kenilworth Road, London, HA8 8XA, United Kingdom

# +44 20 8004 9558 info@ShabbatSmart.com www.ShabbatSmart.com



• Select 'ADD'.

Shabbat

• On SET TIME menu, select 'SUNSET'.

18:33	.11 🗢 🕞	18:33		.11 🗢 💽	18:35 <b>-</b>	.11 🗢 🗖
< Shelly	<b>••</b>	<	Shally	•	SET TIME	
Image: Shabbatsmart         Image: Shabbatsmatsmart         Image: Shabba	ن الternet/Security (أ) Settings	ENABLE SU Shelly reli- given timu have com was able	Weekly Schedule CHEDULE TIMER ay can turn automatically ection to the Internet and to synchronize the time. ADD	on/off at / if you d Shelly	Sunset Time Sunrise Sunset SELECT COMMA ON CHOOSE DAY MON TUE WED	ND THU FRI SAT SUN SAVE CANCEL

85 Kenilworth Road, London, HA8 8XA, United Kingdom

## +44 20 8004 9558 info@ShabbatSmart.com www.ShabbatSmart.com



Shabbat

- Set the time to -40 Minutes.
- SELECT COMMAND, set ON
- CHOOSE DAY, select Friday. And save.
- Select 'ADD'.
- On set time menu, select 'SUNSET
- Set the time to +1:20h.
- SELECT COMMAND, set OFF
- CHOOSE DAY, select Saturday. And save.



85 Kenilworth Road, London, HA8 8XA, United Kingdom

0	+44 20 8004 9558
@	info@ShabbatSmart.com
	www.ShabbatSmart.com



The ShabbatSmart Controller will now enter Shabbat Mode 40 minutes before sunset on Friday, and terminate Shabbat Mode 80 minutes after sunset on Shabbat. (Please note that actions will only take place if the device is connected to the internet)

